


# Phaser 3125/N Black & White Laser Printer High on quality, low on cost

The Phaser 3125/N laser printer delivers high-quality print dependability at a very competitive price. With its compact size and efficient operation, this easy-to-use laser printer supports the print needs of busy offices on a budget.





# Quality streamlined

- Up to 24 ppm (A4) laser printing.
- No waiting with speedy warm-up of less than 15 seconds and fast first-page out times.
- A 400 MHz processor has the power to tackle even complex print jobs.
- With USB and Parallel, plus a 10/100Base-TX Ethernet configuration, you can easily connect one user or many.

## **User-friendly**

- Compact and convenient, it's scaled perfectly for the single-user or small office.
- Print features such as watermarks, N-up, posters, and booklets and support for a wide range of media, simplify customised projects.
- $\bullet$  Deep 250-sheet paper tray lets you do  $\alpha$  lot of printing without interruption.
- Dependable, robust construction, with a high duty cycle.
- Installs in four mouse clicks; networked models can be installed, configured, and managed over the web.
- Status monitor provides alerts if problems occur during printing.

## **Affordable**

- Affordable for even the most cost-conscious.
- Auto Tray Selection and Job Cancel features ensure your job gets printed right.

# Specifications of Phaser 3125/N

### Print Function

Print Speed	Up to 24 ppm (A4)
Print Resolution	Up to 1200 x 1200 Image Quality
First-page-out Time	As fast as 9 seconds
Warm-up Time	Less than 15 seconds
Memory	32 MB
Processor	400 MHz
PDL	PCL6, PostScript 3 compatible
Connectivity	Parallel, USB 2.0, Ethernet 10/100Base-TX
Paper Input Capacity	Bypass Tray: 1 sheet; Main Tray: 250 sheets
Input Paper Size	A4, A5, A6, ISO B5, JIS B5, Letter, Legal, Executive, Folio, Oficio
Input Paper Weight	60 - 163 gsm
Media Types	Plain Paper, Envelopes, Labels, Transparencies, Card Stock
Media Output Capacity	100 sheets
Operating System	Windows 2000/ XP (32/64bit)/ Vista/ Server 2003
	Mac OS 8.6 - 9.2/ 10.1 - 10.5,
	Linux: Red Hat, Fedora Core, Mandrake, SuSE
Monthly Duty Cycle	Up to 20,000 pages
Features	Xerox Status Monitor, Watermarks, Poster Printing, N-Up, Fit to Page, Scaling, Overlays, Auto Tray Select, Toner Save Mode
Device Management	CentreWare Internet Services, CentreWare Web, Xerox Status Monitor,
	Printer settings Utility, SetIP
Dimensions (W x D x H)	358 x 298 x 253 mm
Weight	8.9 kg
Power Supply	110 - 127 VAC, 50/ 60 Hz, 5.5A;
	220 - 240 VAC, 50/ 60 Hz, 3A
Power Consumption	Average: 390 W, Standby: 65 W, Power Saver Mode: 6.5 W
Environment	Temperature: 10 °C - 32 °C; Humidity: 20 % - 80 % RH
Noise Levels	Standby mode: Less than 35 dBA
	Printing mode: Less than 53 dBA
Warranty	Please check with your Fuji Xerox Printers reseller for more information

#### Consumables

Print Cartridge (up to 3,000 pages*)	CWAA0759

\* Average standard pages. Declared yield in accordance with ISO/ IEC 19752 Yield will vary depending on image, area and coverage and print mode. Printer is shipped with one starter print cartridge, average yield 1000 standard pages.

Descriptions in this material, product specifications and/or appearances are subject to change without prior notice due to improvements. Please note that the product colour appears differently from the actual colour as a result of properties of papers or printing ink. Windows and Windows NT are registered trademarks of Microsoft Corporation. NetWore is a registered trademark of Novell, Inc. in the United States. Macintosh, Mac OS and Ether Talk are trademarks of Apple Computer, Inc. PostScript is a registered trademark of Adobe Systems Incorporated in each country, HP-GL is a registered trademark of Hewlett Packard Company. BMLinks is a trademark of the Japan Business Machine and Information System Industries Association (IBMIA). Other company names or product names are registered trademarks or trademarks or trademarks or trademarks.



For Your Safe Use

Before using the product, read the Instruction Manual carefully for proper use.

Use the product with an appropriate adequate power source and voltage displayed. Be sure to establish a ground. In the case of a failure or short circuit, an electric shock may result.

For more information or detailed product specifications, call or visit us at

Fuji Xerox Asia Pacific Pte. Ltd. (993478-A) (Fuji Xerox Printers) Wisma Fuji Xerox, 1st Floor, No. 10, Jalan Bersatu 13/4, 46200 Petaling Jaya, Selangor, Malaysia. Tel: 03-7882 2888 Fax: 03-7882 2767

Service Hotline: 1800 88 1063 www.fujixeroxprinters.com.my

